

ANT2000

WIRELESS / WIFI ANTENNA



A wide range of wireless and other antennae are available from Sensata, including ATEX rated antennae for hazardous areas.

The ANT2000 is typically used on the IWR-PORT and IWT-128 units when they are installed in non-metallic enclosures so that wireless transmission through the panel is not a problem. The connection is an SMA male.

Another application is to increase the range of WiFi enabled products such as routers and wireless bridges.

The ANT2000 has a gain of 5dBi giving it an excellent omni-directional performance in a very small package.

It has a nominal 50 ohm impedance and a VSWR rating of <1.6.

For a full listing of devices available or technical assistance in choosing a suitable antenna please contact Sensata.

Features

- Miniature 5dBi 2.4GHz antenna
- High gain small size
- SMA Male connector
- 2W maximum power
- For higher gain and outdoor antennae see ANT3000 & ANT4000

SPECIFICATIONS


Technical

Type	Co-linear Dipole Array
Frequency Range	2300 - 2500 MHz
Impedance	50Ω Nominal
Gain	5 dBi (+/- 0.5 dBi)
Max Power	2 Watts (CW) at 50°C
Polarization	Vertical
Connector	SMA Male
Operating Temp	-40°C to +85°C



DIMENSIONS

All dimensions are in millimeters.





Part Number: ANT2000

Impedance: 50 ohm

Gain: 5dBi

Made in the UK

Page 3

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

EUROPE
+44 (0)1202 897969
c3w_sales@sensata.com
Cynergy3 Components Ltd.
7 Cobham Road,
Ferndown Industrial Estate,
Wimborne, Dorset,
BH21 7PE, United Kingdom

USA
+1 310 561 8092 / +1 866 258 5057
c3w_sales@sensata.com